

### G + 4 Collective/Selective Microprocessor controller site wiring numbers - Per Floor Reed System

No	Details	No	Details
1.	Display A Segment	060.	Landing UP Call Push Button G Floor
2.	Display B Segment	061.	Landing UP Call Push Button 1st Floor
3.	Display C Segment	062.	Landing UP Call Push Button 2nd Floor
4.	Display D Segment	063.	Landing UP Call Push Button 3rd Floor
5.	Display E Segment	71.	LED DN Supply 1st Floor
6.	Display F Segment	72.	LED DN Supply 2nd Floor
7.	Display G Segment	73.	LED DN Supply 3rd Floor
8.	Display Common 12 V +VE	74.	LED DN Supply 4th Floor
9.	12 V +VE (BUZZER COMMON)	070.	LED UP Supply G Floor
10.	12 V -VE	071.	LED UP Supply 1st Floor
11.	R3-Phase Input 415V AC	072.	LED UP Supply 2nd Floor
12.	Y3-Phase Input 415V AC	073.	LED UP Supply 3rd Floor
13.	B3-Phase Input 415V AC	40.	Car LED Supply G Floor
14.	A3-Phase Output 415V AC	41.	Car LED Supply 1st Floor
15.	B3-Phase Output 415V AC	42.	Car LED Supply 2nd Floor
16.	C3-Phase Output 415V AC	43.	Car LED Supply 3rd Floor
17.	Neutral	44.	Car LED Supply 4th Floor
18.	Car Gate Interlock 12 V -VE	80.	Reeds Supply G Floor
018-018.	Landing Gate Interlock 110V AC	81.	Reeds Supply 1st Floor
19.	Auto/Attend 12V -VE	82.	Reeds Supply 2nd Floor
20.	Door Open Buzzer 12V -VE	83.	Reeds Supply 3rd Floor
21.	Hall Call Buzzer 12V -VE	84.	Reeds Supply 4th Floor
22.	UP Arrow 12V -VE	100.	Car Button Common Supply 12V -VE
23.	DN Arrow 12V -VE	101.	Leading Button Common Supply 12V -VE
24.	Arrow Common 12V +VE	102.	LED Common Supply 12V +VE
25.	110/220 V +VE Brake Supply	103.	Reeds Common Supply 12V -VE
26.	110/220 V -VE Brake Supply	104.	Auto Fan Supply 230V Phase
28.	Final Limit Switch NEUTRAL	110.	Fire Man Switch Supply
28.	Final Limit Switch NEUTRAL	17.	Neutral 230V AC MICROPROCESSOR SUPPLY
29.	110/220 V +VE Retiring CAM Supply	27.	Phase 230V AC MICROPROCESSOR SUPPLY
30.	110/220 V -VE Retiring CAM Supply	330.	UP Final Reed Supply
31.	Inch UP Supply 12V -VE	340.	DN Final Reed Supply
32.	Inch DN Supply 12V -VE	*	V3F Drive Connection
01.	Inch Common Supply 12V -VE	90.	DCM (Drive Common)
35.	Stop Supply 12V -VE (NC)	91.	FWD (Forward)
50.	Car Call Push Button G Floor	92.	RED (Reverse)
51.	Car Call Push Button 1st Floor	93.	B1 Direct Connection To Breaking Register From Drive
52.	Car Call Push Button 2nd Floor	94.	B2 Direct Connection To Breaking Register From Drive
53.	Car Call Push Button 3rd Floor	95.	RA (C - Common)
54.	Car Call Push Button 4th Floor	96.	RC (NO - Normally Open)
61.	Landing DN Call Push Button 1st Floor	97.	SECOND SPEED COMMAND
62.	Landing DN Call Push Button 2nd Floor	11.	INPUT   14.  OUTPUT
63.	Landing DN Call Push Button 3rd Floor	12.	INPUT   15.  OUTPUT
64.	Landing DN Call Push Button 4th Floor	13.	INPUT   16.  OUTPUT